

FOR WIRE, CABLE, PIPE AND TUBE



> Clear print at high speeds

The Taymer I100 Indent Printer is designed for printing in one meter or two feet intervals. The Taymer 6-digit sequential counter is standard on the I100 printer. Its industry leading design minimizes maintenance requirements. The heat transfer system is capable of producing clear, durable legends at speeds of up 500 feet or 200 meters per minute.

> Easy to set up and use

The ease of operation and setup reduces scrap, production delays and the risk of damage to delicate communication and fiber optic cables. The I100's robust construction and extra cable guides ensure consistent, high print quality even on rigid power cables.

> Cost saving features

The ease of operation and setup reduces scrap, production delays and the risk of damage to delicate communication and fiber optic cables. The I100's robust construction and extra cable guides ensure consistent, high print quality even on rigid power cables.

FEATURES

- > Pushbutton, on the fly counter reset
- > Cost efficient legend segment mounting system
- > PLC control system reduces and simplifies maintenance requirements
- > Casters provide easy movement in and out of the line
- > Rugged, heavy duty construction for the production environment
- > Spring-loaded guide rollers allow trouble free passage of cable bulges



SPECIFICATIONS

- Cable size:
0.2" to 5" OD - 5.0 mm to 127 mm OD
Larger sizes available
- Maximum speed:
up to 500 feet per minute or up to 200
- Drum drive:
Direct drive
- Print interval accuracy:
0.9%
- Type form:
Engraved steel, hardened
- Character height:
0.0625" to 3125" - 1.6 mm to 8.0 mm
- Print legend length:
7 characters per inch
24 characters per 100mm
- Compressed air:
80-100 PSI, dry
- Print temperature:
Closed Loop P.I.D. Controller
- Sequential marking:
6 digit
- Counter reset:
On the fly, electronic pushbutton
- Print Interval:
1 Meter or 2 Feet
- Print interval:
1 m or 2 ft
- Jacket materials:
Most common jacket materials
- Power requirements:
208 - 240 VAC 16A, single phase, 50/60 Hz

TAYMER

☎ +1 905 479 2614

✉ info@taymer.com

Send samples to:

Taymer International Inc.
208 Telson Road
Markham, ON L3R 1E6
CANADA